

Autonomous addressing board for PILOTBOX

Control addressing board for PILOTBOX



MODE	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
------	-------	-------	-------	-------	-------	-------	-------	-------	-------	--------

AUTONOMOUS - FIXED

Red channel	OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	ON
Green channel	ON	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	ON
Blue channel	OFF	OFF	ON	OFF	OFF	OFF	OFF	OFF	ON	ON
Magenta channel	OFF	ON	ON	OFF	OFF	OFF	OFF	OFF	ON	ON
Yellow channel	ON	ON	ON	OFF	OFF	OFF	OFF	OFF	ON	ON
Cyan channel	OFF	OFF	OFF	ON	OFF	OFF	OFF	OFF	ON	ON
All channels	ON	OFF	ON	OFF	OFF	OFF	OFF	OFF	ON	ON

AUTONOMOUS - RGB

2 Sec.	OFF	ON	OFF	ON	OFF	OFF	OFF	OFF	ON	ON
5 Sec.	ON	ON	OFF	ON	OFF	OFF	OFF	OFF	ON	ON
10 Sec.	OFF	OFF	ON	ON	OFF	OFF	OFF	OFF	ON	ON
30 Sec.	ON	OFF	ON	ON	OFF	OFF	OFF	OFF	ON	ON
1 Minute	OFF	ON	ON	ON	OFF	OFF	OFF	OFF	ON	ON
5 Minutes	ON	ON	ON	ON	OFF	OFF	OFF	OFF	ON	ON
30 Minutes	OFF	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON	ON
1 Hour	ON	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON	ON

AUTONOMOUS - PASTEL

2 Sec.	OFF	OFF	ON	OFF	ON	OFF	OFF	OFF	ON	ON
5 Sec.	ON	OFF	ON	OFF	ON	OFF	OFF	OFF	ON	ON
10 Sec.	OFF	ON	ON	OFF	ON	OFF	OFF	OFF	ON	ON
30 Sec.	ON	ON	ON	OFF	ON	OFF	OFF	OFF	ON	ON
1 Minute	OFF	OFF	OFF	ON	ON	OFF	OFF	OFF	ON	ON
5 Minutes	ON	OFF	OFF	ON	ON	OFF	OFF	OFF	ON	ON
30 Minutes	OFF	ON	OFF	ON	ON	OFF	OFF	OFF	ON	ON
1 Hour	ON	ON	OFF	ON	ON	OFF	OFF	OFF	ON	ON

AUTONOMOUS - RANDOM

2 Sec.	OFF	ON	OFF	ON	OFF	ON	OFF	OFF	ON	ON
5 Sec.	ON	ON	OFF	ON	OFF	ON	OFF	OFF	ON	ON
10 Sec.	OFF	OFF	ON	ON	OFF	ON	OFF	OFF	ON	ON
30 Sec.	ON	OFF	ON	ON	OFF	ON	OFF	OFF	ON	ON
1 Minute	OFF	ON	ON	ON	OFF	ON	OFF	OFF	ON	ON
5 Minutes	ON	ON	ON	ON	OFF	ON	OFF	OFF	ON	ON
30 Minutes	OFF	OFF	OFF	OFF	ON	ON	OFF	OFF	ON	ON
1 Hour	ON	OFF	OFF	OFF	ON	ON	OFF	OFF	ON	ON

MODE	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
DMX	X	X	X	X	X	X	X	X	X	OFF

X : Choose binary addressing

ADDRESSING - DIP SWITCH COMBINATION TABLE (3 CHANNELS)

MODE	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
------	-------	-------	-------	-------	-------	-------	-------	-------	-------	--------

DMX - FORCED ADDRESSING

Address 1	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
Address 2	OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
Address 3	ON	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
Address 4	OFF	OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF
Address 510	OFF	ON	ON	ON	ON	ON	ON	ON	ON	OFF

DMX - Auto Addressed RDM	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
--------------------------	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----

MODE	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
DALI	OFF	OFF	OFF	OFF	OFF	OFF	OFF	ON	OFF	ON

POTENTIOMETER OR PUSH BUTTON: THE MODE OF THE DEVICE USING THE DIPSWITCHES

MODE	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
------	-------	-------	-------	-------	-------	-------	-------	-------	-------	--------

POTENTIOMETER 100KΩ

RGB	OFF	OFF	OFF	OFF	OFF	OFF	OFF	ON	ON	ON
Mono.	OFF	ON	OFF	OFF	OFF	OFF	OFF	ON	ON	ON

PUSH BUTTON

RGB	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	ON	ON
Mono.	ON	ON	OFF	OFF	OFF	OFF	OFF	ON	ON	ON